

FEATURES:

RE 102

- ☞ Rugged CRCA sheet with powder coated finish.
- ☞ Operates on 220v, 50Hz AC supply.
- ☞ Standby battery back up with built in charging.
- ☞ Fire / Fault status in unambiguous colored LED indication.
- ☞ Switch Mode Power Supply.
- ☞ Tactile key pad for easy panel operation.
- ☞ System on indication.
- ☞ Main, Standby status indication.
- ☞ Low Battery visual warning with audible tone.
- ☞ Relay output for actuators for Fire and Fault.
- ☞ Lamp Test facility.
- ☞ Zone wise one man Walk Test facility.
- ☞ Zone wise Isolation facility with loop voltage cut off.
- ☞ Compatible to all types of conventional detectors.



TECHNICAL DATA

1. Power Supply:	AC Input Supply	:	220 V AC, 50Hz
	DC Input Supply	:	24 V DC
2. Operating Conditions		:	-10 to 45 °C, 95 % RH Max.
3. Operating Voltage		:	24 V DC
4. Normal Loop Voltage		:	20.7 DC
5. Open Threshold Current		:	4.2 mA
6. Short Circuit Threshold Current		:	40 mA
7. Stand by Threshold Current (EOL Current + detector's Current)		:	8.2 mA
8. Alarm Current		:	20 - 35 mA
9. Quiescent Current		:	60mA
10. Colour of the Panel		:	Broken White (Red, Red Texure - Optional)
11. Panel Size		:	350 X 250 X 100(Width X Height X Depth)
12. Approximate Weight		:	4Kgs.
13. ALARM OUTPUT:			
	Common Hooter Output	:	24V@1A.
14. REMOTE OUTPUTS:			
	Outputs	:	Fire, Fault Relay Contacts (30V AC/ DC @ 2A contact).